

(19) World Intellectual Property
Organization
International Bureau



(43) International Publication Date
27 May 2004 (27.05.2004)


PCT

(10) International Publication Number
WO 2004/045239 A3

- (51) International Patent Classification⁷: **H04Q 7/38**
- (21) International Application Number:
PCT/US2003/036085
- (22) International Filing Date:
7 November 2003 (07.11.2003)
- (25) Filing Language: English
- (26) Publication Language: English
- (30) Priority Data:
10/295,659 14 November 2002 (14.11.2002) US
10/295,660 14 November 2002 (14.11.2002) US
- (71) Applicant: **QUALCOMM INCORPORATED** [US/US];
5775 Morehouse Drive, San Diego, CA 92121 (US).
- (72) Inventors: **ATTAR, Rashid, A.**; 8520 Costa Verde Boulevard, #3112, San Diego, CA 92122 (US). **LOTT, Christopher, G.**; 3783 Balboa Terrace, #C, San Diego, CA 92117 (US).
- (74) Agents: **WADSWORTH, Philip, R.** et al.; Qualcomm Incorporated, 5775 Morehouse Drive, San Diego, CA 92121 (US).
- (81) Designated States (*national*): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NI, NO, NZ, OM, PG, PH, PL, PT, RO, RU, SC, SD, SE, SG, SK, SL, SY, TJ, TM, TN, TR, TT, TZ, UA, UG, UZ, VC, VN, YU, ZA, ZM, ZW.
- (84) Designated States (*regional*): ARIPO patent (BW, GH, GM, KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IT, LU, MC, NL, PT, RO, SE, SI, SK, TR), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).
- Published:
— with international search report

[Continued on next page]

(54) Title: WIRELESS COMMUNICATION RATE SHAPING



(57) Abstract: Reverse Link (RL) data rate allocation in a High Data Rate (such as 1xEV-DO) system as a function of Forward Link (FL) channel quality. Rate shaping of a throughput profile for multiple Access Terminals (ATs) is performed by adjusting transition probabilities associated with a data rate allocation algorithm. The RL maximum data rate per AT is adjusted to reduce the loading in a designated area and result in rate shaping of the cell and/or sector. In one embodiment, the maximum data rates are adjusted as a function of the FL Signal to Interference and Noise Ratio (SINR), such as measured per serving sector or as a captured sum total of FL SINR. In still another embodiment, the maximum data rates are adjusted as a function of differences in rise-over-thermal values between neighboring sectors.

BEST AVAILABLE COPY

WO 2004/045239 A3



— *before the expiration of the time limit for amending the claims and to be republished in the event of receipt of amendments*

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

(88) Date of publication of the international search report:
23 September 2004

INTERNATIONAL SEARCH REPORT

Int'l Application No

PCT/US 03/36085

A. CLASSIFICATION OF SUBJECT MATTER
IPC 7 H04Q7/38

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 7 H04Q H04B

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

EPO-Internal, WPI Data

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	WO 99/23844 A (QUALCOMM INC) 14 May 1999 (1999-05-14)	1,2,4,5, 8,11,19, 20
Y	page 5, line 32 - page 6, line 6 page 36, line 34 - page 37, line 32 page 40, line 32 - page 41, line 21 page 44, line 12 - page 45, line 11 page 46, line 15 - page 47, line 9 figure 28 table 5 ----- -/--	3

☒ Further documents are listed in the continuation of box C.☒ Patent family members are listed in annex.

* Special categories of cited documents :

- *A* document defining the general state of the art which is not considered to be of particular relevance
- *E* earlier document but published on or after the international filing date
- *L* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- *O* document referring to an oral disclosure, use, exhibition or other means
- *P* document published prior to the international filing date but later than the priority date claimed

- *T* later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
- *X* document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
- *Y* document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.
- *G* document member of the same patent family

Date of the actual completion of the international search

20 July 2004

Date of mailing of the international search report

16.08.04

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,
Fax: (+31-70) 340-3016

Authorized officer

Rosenauer, H

INTERNATIONAL SEARCH REPORT

Int. Application No

PCT/US 03/36085

C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
Y A	US 5 442 625 A (GITLIN RICHARD DENNIS ET AL) 15 August 1995 (1995-08-15) column 1, line 7 - line 10 column 1, line 45 - line 59 column 6, line 48 - line 66 column 7, line 33 - line 37 figures 1,5 -----	3 1-21, 33-36
X	EP 1 231 807 A (LG ELECTRONICS INC) 14 August 2002 (2002-08-14) page 4, line 31 - line 36 page 5, line 3 - page 6, line 7 page 6, line 49 - line 54 page 7, line 20 - line 39 page 7, line 55 - page 8, line 7 figures 2,3,5,6,8 -----	6,13
X Y	US 2002/015388 A1 (CHOI HO-KYU ET AL) 7 February 2002 (2002-02-07) page 1, paragraph 3 page 1, paragraph 10 - paragraph 11 page 3, paragraph 29 - paragraph 33 page 5, paragraph 65 - page 6, paragraph 79 figure 6 -----	6,13 7,16,21
Y	EP 1 077 580 A (LUCENT TECHNOLOGIES INC) 21 February 2001 (2001-02-21) page 3, paragraph 7 page 5, paragraph 18 - page 6, paragraph 25 figures 1-3 -----	7,16,21
A	WO 00/38348 A (NOKIA NETWORKS OY ;LAAKSO JANNÉ (FI)) 29 June 2000 (2000-06-29) page 6, line 16 - page 7, line 30 page 19, line 14 - line 25 page 22, line 16 - page 23, line 16 page 25, line 9 - page 28, line 17 page 29, line 9 - line 21 page 31, line 5 - line 25 page 41, line 1 - line 24 page 43, line 13 - page 44, line 30 page 48, line 8 - line 16 figures 1,3A-3C ----- -/--	7,16,21

INTERNATIONAL SEARCH REPORT

International Application No.

PCT/US 03/36085

C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	US 2002/159395 A1 (HOFFMANN JOHN E ET AL) 31 October 2002 (2002-10-31) page 1, paragraph 6 - paragraph 9 page 3, paragraph 29 page 4, paragraph 49 page 5, paragraph 74 - page 6, paragraph 76 page 9, paragraph 124 - paragraph 129 figures 1,8	1-21, 33-36
A	WO 00/14900 A (QUALCOMM INC) 16 March 2000 (2000-03-16) page 1, line 7 - line 9 page 16, line 30 - page 19, line 30 figures 1,2,6	1-21, 33-36
X	WO 01/24004 A (QUALCOMM INC) 5 April 2001 (2001-04-05)	22,23, 26,27, 30-32, 33-36
A	page 1, line 6 - line 8 page 5, line 10 - page 6, line 6 page 7, line 7 - page 8, line 16 page 7, line 22 - page 10, line 8 page 10, line 23 - page 11, line 22 figures 2,4,5	
A	WO 01/03357 A (QUALCOMM INC) 11 January 2001 (2001-01-11) page 9, line 9 - page 10, line 30 page 14, line 16 - page 15, line 8 figures 1,3	22-32
A	WO 01/24568 A (QUALCOMM INC) 5 April 2001 (2001-04-05) page 1, line 7 - line 10 page 5, line 3 - line 25 page 12, line 22 - page 13, line 31 figures 1F,2	22-32

INTERNATIONAL SEARCH REPORT

national application No.
PCT/US 03/36085

Box I Observations where certain claims were found unsearchable (Continuation of item 1 of first sheet)

This International Search Report has not been established in respect of certain claims under Article 17(2)(a) for the following reasons:

1. ☐ Claims Nos.:
because they relate to subject matter not required to be searched by this Authority, namely:
2. ☐ Claims Nos.:
because they relate to parts of the International Application that do not comply with the prescribed requirements to such an extent that no meaningful International Search can be carried out, specifically:
3. ☐ Claims Nos.:
because they are dependent claims and are not drafted in accordance with the second and third sentences of Rule 6.4(a).

Box II Observations where unity of invention is lacking (Continuation of item 2 of first sheet)

This International Searching Authority found multiple inventions in this international application, as follows:

see additional sheet

1. ☒ As all required additional search fees were timely paid by the applicant, this International Search Report covers all searchable claims.
2. ☐ As all searchable claims could be searched without effort justifying an additional fee, this Authority did not invite payment of any additional fee.
3. ☐ As only some of the required additional search fees were timely paid by the applicant, this International Search Report covers only those claims for which fees were paid, specifically claims Nos.:
4. ☐ No required additional search fees were timely paid by the applicant. Consequently, this International Search Report is restricted to the invention first mentioned in the claims; it is covered by claims Nos.:

Remark on Protest

- ☐ The additional search fees were accompanied by the applicant's protest.
- ☒ No protest accompanied the payment of additional search fees.

FURTHER INFORMATION CONTINUED FROM PCT/ISA/ 210

This International Searching Authority found multiple (groups of) inventions in this international application, as follows:

1. claims: 1-21, 33-36

The first invention relates to methods and corresponding apparatus for determining the channel quality measuring different parameters, determining a maximum reverse link data rate depending on the channel quality. This relates to the problem of how to improve the performance of a wireless communication system.

2. claims: 22-32

This invention concerns, as no advantageous effects could be seen with the prior art disclosed in document D1 methods and corresponding apparatus for providing an alternative solution to determine whether a reverse link rate should be increased or decreased. This problem is solved by transition probabilities corresponding to a plurality of data rates, wherein said transition probabilities are adjusted and applied to determine the change of a reverse link data rate.

INTERNATIONAL SEARCH REPORT

Information on patent family members

International Application No

PCT/US 03/36085

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
WO 9923844	A	14-05-1999	US 2003063583 A1	03-04-2003
			AU 750154 B2	11-07-2002
			AU 1303299 A	24-05-1999
			BR 9813885 A	26-09-2000
			CA 2306868 A1	14-05-1999
			CN 1381997 A	27-11-2002
			CN 1124754 B	15-10-2003
			EP 1326471 A2	09-07-2003
			EP 1434448 A2	30-06-2004
			EP 1029419 A2	23-08-2000
			HU 0100629 A2	28-06-2001
			ID 28082 A	03-05-2001
			JP 2001522211 T	13-11-2001
			NO 20002228 A	03-07-2000
			NZ 503841 A	25-10-2002
			NZ 519543 A	27-02-2004
			NZ 520681 A	27-02-2004
			PL 342656 A1	02-07-2001
			TR 200001200 T2	21-11-2000
			WO 9923844 A2	14-05-1999
			US 2003142656 A1	31-07-2003
			ZA 9810003 A	02-08-2000
US 5442625	A	15-08-1995	CA 2145708 A1	14-11-1995
			EP 0682423 A2	15-11-1995
			JP 8065273 A	08-03-1996
			US 5856971 A	05-01-1999
EP 1231807	A	14-08-2002	KR 2002066590 A	21-08-2002
			KR 2003005899 A	23-01-2003
			KR 2003024442 A	26-03-2003
			CN 1371219 A	25-09-2002
			EP 1231807 A2	14-08-2002
			US 2002141349 A1	03-10-2002
US 2002015388	A1	07-02-2002	KR 2002006588 A	23-01-2002
EP 1077580	A	21-02-2001	US 6456850 B1	24-09-2002
			AU 5196900 A	22-02-2001
			BR 0004560 A	03-04-2001
			CA 2315847 A1	17-02-2001
			CN 1284823 A	21-02-2001
			EP 1077580 A1	21-02-2001
			JP 2001119355 A	27-04-2001
WO 0038348	A	29-06-2000	WO 0038348 A1	29-06-2000
			AU 2415199 A	12-07-2000
			BR 9816103 A	04-09-2001
			CN 1124700 B	15-10-2003
			EP 1142154 A1	10-10-2001
			JP 2002533984 T	08-10-2002
			US 2003003921 A1	02-01-2003
US 2002159395	A1	31-10-2002	NONE	
WO 0014900	A	16-03-2000	US 6597705 B1	22-07-2003
			AU 6036799 A	27-03-2000
			CN 1141802 C	10-03-2004

INTERNATIONAL SEARCH REPORT

Information on patent family members

International Application No

PCT/US 03/36085

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
WO 0014900	A		EP 1112624 A1	04-07-2001
			JP 2002524962 T	06-08-2002
			WO 0014900 A1	16-03-2000
			US 2003193907 A1	16-10-2003
WO 0124004	A	05-04-2001	US 6665272 B1	16-12-2003
			AU 7623400 A	30-04-2001
			BR 0014296 A	27-08-2002
			CA 2384472 A1	05-04-2001
			CN 1377484 T	30-10-2002
			EP 1222538 A2	17-07-2002
			JP 2003510928 T	18-03-2003
			NO 20021505 A	29-05-2002
			TW 539999 B	01-07-2003
			WO 0124004 A2	05-04-2001
WO 0103357	A	11-01-2001	US 6556549 B1	29-04-2003
			AU 5911500 A	22-01-2001
			BR 0011966 A	17-12-2002
			CA 2377060 A1	11-01-2001
			EP 1192749 A1	03-04-2002
			JP 2003521847 T	15-07-2003
			NO 20016409 A	24-01-2002
			WO 0103357 A1	11-01-2001
			US 2003072287 A1	17-04-2003
			US 2003076795 A1	24-04-2003
			US 2003112774 A1	19-06-2003
WO 0124568	A	05-04-2001	US 6563810 B1	13-05-2003
			AU 7623300 A	30-04-2001
			BR 0014397 A	20-08-2002
			CN 1377562 T	30-10-2002
			EP 1216595 A1	26-06-2002
			JP 2003510991 T	18-03-2003
			TW 484334 B	21-04-2002
			WO 0124568 A1	05-04-2001
			US 2003133409 A1	17-07-2003

(19) World Intellectual Property
Organization
International Bureau



(43) International Publication Date
27 May 2004 (27.05.2004)


PCT

(10) International Publication Number
WO 2004/045239 A2

- (51) International Patent Classification⁷: **H04Q 7/38**, 7/32, H04B 7/005
- (21) International Application Number: PCT/US2003/036085
- (22) International Filing Date: 7 November 2003 (07.11.2003)
- (25) Filing Language: English
- (26) Publication Language: English
- (30) Priority Data:
10/295,659 14 November 2002 (14.11.2002) US
10/295,660 14 November 2002 (14.11.2002) US
- (71) Applicant: **QUALCOMM INCORPORATED** [US/US]; 5775 Morehouse Drive, San Diego, CA 92121 (US).
- (72) Inventors: **ATTAR, Rashid, A.**; 8520 Costa Verde Boulevard, #3112, San Diego, CA 92122 (US). **LOTT, Christopher, G.**; 3783 Balboa Terrace, #C, San Diego, CA 92117 (US).
- (74) Agents: **WADSWORTH, Philip, R.** et al.; Qualcomm Incorporated, 5775 Morehouse Drive, San Diego, CA 92121 (US).
- (81) Designated States (*national*): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NI, NO, NZ, OM, PG, PH, PL, PT, RO, RU, SC, SD, SE, SG, SK, SL, SY, TJ, TM, TN, TR, TT, TZ, UA, UG, UZ, VC, VN, YU, ZA, ZM, ZW.
- (84) Designated States (*regional*): ARIPO patent (BW, GH, GM, KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IT, LU, MC, NL, PT, RO, SE, SI, SK, TR), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).
- Published:
— without international search report and to be republished upon receipt of that report

[Continued on next page]

(54) Title: WIRELESS COMMUNICATION RATE SHAPING



(57) Abstract: Reverse Link (RL) data rate allocation in a High Data Rate (such as 1xEV-DO) system as a function of Forward Link (FL) channel quality. Rate shaping of a throughput profile for multiple Access Terminals (ATs) is performed by adjusting transition probabilities associated with a data rate allocation algorithm. The RL maximum data rate per AT is adjusted to reduce the loading in a designated area and result in rate shaping of the cell and/or sector. In one embodiment, the maximum data rates are adjusted as a function of the FL Signal to Interference and Noise Ratio (SINR), such as measured per serving sector or as a captured sum total of FL SINR. In still another embodiment, the maximum data rates are adjusted as a function of differences in riseover-thermal values between neighboring sectors.

WO 2004/045239 A2



For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

WIRELESS COMMUNICATION RATE SHAPING

Reference to Co-Pending Applications for Patent

- [0001] The present Application for Patent is related to U.S. Patent Application No. 10/295,660, filed November 14, 2002, entitled, "WIRELESS COMMUNICATION RATE SHAPING," by Attar et al., assigned to the assignee hereof, and expressly incorporated by reference herein.

BACKGROUND

Field

- [0002] The present invention relates generally to wireless communication, and particularly to reverse link rate allocation for packet data transmissions.

Background

- [0003] In a wireless communication system, such as a system supporting packetized data communications, a radio link for transmissions from an Access Network (AN), or system infrastructure, to an Access Terminal, or remote user, is referred to as a downlink or Forward Link (FL). The radio link for transmissions from the AT to the AN is referred to as the uplink or Reverse Link (RL). Each AT determines an appropriate data rate for RL transmissions. Various methods for determining RL transmission rates from an AT are discussed in "SYSTEM AND METHOD FOR PERSISTENCE-VECTOR-BASED MODIFICATION OF USAGE RATES," by Rajesh Pankaj, et al., having U.S. Patent Application No. 09/410,199, filed on September 30, 1999, and assigned to the assignee hereof.
- [0004] In a High Data Rate system, such as a system supporting the "cdma2000 High Rate Packet Data Air Interface Specification," referred to herein as "1xEV-DO," or IS-856, the AT autonomously determines a data rate for transmissions on the RL based on a probabilistic algorithm that considers the amount of data pending, the available transmit power or PA (power amplifier) headroom, the closed loop resource allocation calculation, and the maximum data rate as indicated to the AT by the AN. The AN assigns probabilities to each of the possible rate transitions that an AT may make. Each AT uses the same probabilities, which are predetermined and set at each AT.

[0005] Additionally, each AT implements a power control mechanism to adjust the transmit power dynamically. The adjust in AT transmit power compensates for changes in AT location, shadowing and fading experienced by the AT and the transmit data rate. As an AT moves farther away from a Base Station (BS) in the Active Set (AS) of the AT, the transmit power of the AT increases to compensate. Generally, as an AT moves toward a sector boundary, the interference caused by the AT in question to other AT's is increased due to an increase in the AT transmit power.

[0006] As the rate allocation algorithm considers the transmit power, an AT far from the AN, or otherwise experiencing a poor channel condition, relative to other ATs, may be subject to low data rates for an extended time period. In many communication systems, however, there is a desire to provide an equal grade of service. In other words, each AT is provided an approximately equal opportunity to transmit data on the RL without regard to channel condition so as not to penalize an AT for moving within the system. However, this mechanism does not take into account the interference due to an AT.

[0007] An increase in data rate results in an increase in the interference caused by an AT to other ATs in the system and therefore, there is a desire to discourage and/or prohibit that AT from transmitting at higher rates if that AT is likely to cause excessive interference to other AT's in the system. Further, there is a desire for each AT to transmit at maximum rate conditioned on equal interference considering all ATs in the system.

[0008] There is a need, therefore, for AT rate allocation that balances an equal grade of service goal with the desire to maximize capacity of the system. Similarly, there is a need for AT rate allocation that provides a robust RL and reduces interference to other users. There is further a need for reverse link rate allocation to achieve better control over other-cell interference and improve system stability.

BRIEF DESCRIPTION OF THE DRAWINGS

[0009] FIG. 1 is a cellular communication system supporting packetized data transmissions.

[0010] FIG. 2A is an illustration of a throughput profile as a function of forward link channel quality for multiple access terminals.

- [0011] FIG. 2B is an illustration of a rate profile for the reverse link in a wireless communication system.
- [0012] FIG. 3 is a table of data rates available in a communication system.
- [0013] FIG. 4 is an illustration of transition probabilities used for reverse link rate allocation in a communication system.
- [0014] FIG. 5 is a graph of reverse activity bits in a high data rate communication system.
- [0015] FIG. 6 is an illustration of transition probabilities in a wireless communication system.
- [0016] FIG. 7 is a table for determining a maximum reverse link data rate as a function of forward link signal to interference and noise ratio.
- [0017] FIG. 8 is an Access Terminal.
- [0018] FIG. 9 is an infrastructure element of an Access Network.

DETAILED DESCRIPTION

- [0019] The field of wireless communications has many applications including, e.g., cordless telephones, paging, wireless local loops, Personal Digital Assistants (PDAs), Internet telephony, and satellite communication systems. A particularly important application is cellular telephone systems for mobile subscribers. As used herein, the term "cellular" system encompasses both cellular and Personal Communication Services (PCS) frequencies. Various over-the-air interfaces have been developed for such cellular telephone systems including, e.g., Frequency Division Multiple Access (FDMA), Time Division Multiple Access (TDMA), and Code Division Multiple Access (CDMA). In connection therewith, various domestic and international standards have been established including, e.g., Advanced Mobile Phone Service (AMPS), Global System for Mobile (GSM), and Interim Standard 95 (IS-95). IS-95 and its derivatives, IS-95A, IS-95B, ANSI J-STD-008 (often referred to collectively herein as IS-95), and proposed high-data-rate systems are promulgated by the Telecommunication Industry Association (TIA) and other well-known standards bodies.
- [0020] Cellular telephone systems configured in accordance with the use of the IS-95 standard employ CDMA signal processing techniques to provide highly efficient and robust cellular telephone service. Exemplary cellular telephone systems configured

substantially in accordance with the use of the IS-95 standard are described in U.S. Patent Nos. 5,103,459 and 4,901,307, which are assigned to the assignee of the present invention. An exemplary system utilizing CDMA techniques is the cdma2000 ITU-R Radio Transmission Technology (RTT) Candidate Submission (referred to herein as cdma2000), issued by the TIA. The standard for cdma2000 is given in the draft versions of IS-2000 and has been approved by the TIA and 3GPP2. Another CDMA standard is the W-CDMA standard, as embodied in 3rd Generation Partnership Project "3GPP", Document Nos. 3G TS 25.211, 3G TS 25.212, 3G TS 25.213, and 3G TS 25.214. The telecommunication standards cited above are examples of only some of the various communication systems that can be implemented.

[0021] FIG. 1 illustrates a cellular communication system 100 according to one embodiment. The system 100 includes multiple cells, each covering a geographical area. Each of the multiple cells includes multiple sectors. For example, cell 110 includes the sectors 112, 114, and 116. Each of the sectors is defined by an antenna. As illustrated, the antenna element 120 is directed within the sector 112; the antenna element 122 is directed within the sector 114; and the antenna element 124 is directed within the sector 116. Examples of further antenna structures and base station arrangements are illustrated in FIG. 1. The system 100 is provided as an example for the following discussion. Note that alternate systems may implement alternate arrangements and configurations, wherein the number of antenna elements per sector and the number of sectors per cell may vary. Note that alternate embodiments may have different terminology for similar functional units, and may incorporate different configurations of components and functional units.

[0022] FIG. 2A illustrates a plot of the throughput for each of multiple ATs in the system 100 as a function of an associated FL channel quality. The shape of the plot reflects a RL profile for the ATs in the system. As illustrated, the throughput of an AT is approximately proportional to the serving sector FL Signal-to-Interference and Noise Ratio (SINR). Generally, the closer an AT is to a sector antenna, the higher the SINR and therefore, the higher the throughput. These algorithms assume that on an average the channel conditions on the forward and reverse link are symmetric. As illustrated, the current RL rate allocation algorithm does not result in equal grade of service for those ATs located far from a sector antenna.

[0023] When an AT is in soft-handoff its overhead channel and traffic transmissions are decoded at multiple cells. The RL rate shaping can be based on criteria other than FL serving sector SINR. The rate shaping criteria may be based on a FL captured SINR (i.e., the sum total of the SINR of all pilots in the active set). As discussed hereinbelow, FIG. 2B illustrates a rate profile for the RL considering multiple sectors and multiple mobile stations or ATs. As illustrated, it's a contour plot of RL rate based on FL SINR in a multi-sector layout. The dark areas correspond to the better channel conditions, wherein the channel condition degrades with distance from the transmitter. The sector boundaries are overlaid to the figure.

[0024] It is desirable to determine a RL profile that supports a variety of desired services for multiple ATs in system 100. Note that RL rate shaping should not preclude a mobile station from utilizing a given service. For example, videoconferencing may require 64kbps, and therefore, all mobile stations may be allowed to transmit at 76.8kbps as needed. Providing equal Grade of Service may not be a requirement for all systems. The desired shape of the profile is determined based on the goals and requirements of a given system. The determination of a desired shape of the profile and the implementation of a rate allocation method to achieve the desired shape is generally referred to as "rate shaping." In one embodiment, rate shaping involves dynamic rate allocation at the AT, and specifically modification of the rate allocation algorithm to consider a quality measure of the FL, such as serving sector SINR. Such reverse link rate allocation, also referred to as rate shaping, limits the interference due to terminals in handoff regions. This is achieved either by limiting the max RL rate or by reducing the likelihood that a terminal in handoff regions transmits at the highest rates, wherein terminals in handoff region are allowed to transmit at the highest rates in the case of an unloaded system.

Rate Allocation Algorithm

[0025] The AT implements an algorithm for rate allocation that considers: 1) pending data; 2) available transmit power for traffic as determined based on the difference between the overhead channel transmit power and the maximum transmit power; 3) Closed Loop Resource Allocation (CLRA); and 4) maximum data rate. The algorithm determines a data rate associated with each of the four considerations, and selects the

minimum rate. The AT updates the data rate periodically. In a 1xEV-DO system, the AT updates the data rate every 16 slots, however, alternate systems may implement another scheme for updating the data rate. The pending data has an associated data rate, R_1 , that increases proportionally with the amount of data in a data queue at the AT. The RL data allowed for transmission may be limited by the available PA headroom. This rate $R_2 \leq R_1$. if PA headroom is sufficient to support R_1 , then $R_2 = R_1$; otherwise, $R_2 < R_1$.

[0026] The CLRA, discussed in detail hereinbelow, has an associated data rate R_3 , which is determined based on RL rate transition probabilities. The maximum data rate is identified as R_4 and may be set by the AN.

[0027] The CLRA limits changes in the data rate, and specifically limits increases so as to avoid large increases in data rates by multiple ATs in quick succession that may overload the system. Note that a Reverse Activity Bit (RAB) is a mechanism to identify a RL loaded condition to the AT. The RAB mechanism has a delay incurred by the time(s) required for: 1) measurement of the load at the BS; 2) the subsequent transmission of the RAB to terminals; and 3) implementation at the AT to reduce/increase their data rate. The data rate R_3 associated with the CLRA calculation is determined based on the previous data rate, referred to as R_{old} . Two sets of transition probabilities are provided by the AN. Each set assigns a transition probability to each of the allowable data rates. The first set corresponds to transitions that increase the data rate. The second set corresponds to transitions that decrease the data rate.

[0028] The present instantiation of IS-856 allows five data rates on the RL starting with a minimum rate of 9.6kbps. The rates of one embodiment supporting the 1xEV-DO standard are illustrated in FIG. 3. The rate index identifies each corresponding data rate. Each successive data rate is twice the previous rate. FIG. 4 illustrates the transition probability sets generated in the CLRA calculation. On the top is the first set of transition probabilities, identified as P_{UP} . On the bottom is the second set of transition probabilities, identified as P_{DN} . The indices, such as given in FIG. 3, point to the associated transition probabilities in each set.

[0029] The AN transmits a busy bit, referred to as the Reverse link Activity Bit (RAB). FIG. 5 illustrates the RAB values over time for a given AN. As illustrated, the RAB may be set or cleared depending on the loading of the AN. The RAB is transmitted with

a period T_{RAB} . The RAB setting (1 or 0) indicates to each AT whether or not the system is loaded. For the current discussion assume the RAB is set to indicate a loaded condition and cleared otherwise. Alternate methods may be implemented for conveying reverse link loading information to the AT. When the AT receives the RAB (or other indication that the system is loaded), the AT has two decision options for rate allocation: 1) decrease the data rate; or 2) maintain the current data rate R_{OLD} . In making the decision, the AT applies the second set of transition probabilities. The AT selects the transition probability within the second set P_{DN} that corresponds to the current data rate R_{OLD} .

[0030] If the AT receives a cleared RAB, or other indication that the system is not loaded, the AT has two decision options for rate allocation: 1) increase the data rate; or 2) maintain the current data rate, R_{OLD} . The AT selects a transition probability from the first set P_{UP} . Again the particular transition probability selected corresponds to the current data rate R_{OLD} .

[0031] For each rate allocation update, the AT then generates a random number for comparison to the selected transition probability. The result of the comparison determines which of the two decision options the AT will make. Effectively the transition probability determines the percentage of time a data rate change will be made. Typically, for low data rates the transition probabilities will be higher, wherein any random number less than the transition probability will result in a data rate increase. The transition probabilities are generally constrained as:

$$P1 > P2 > P3 > P4 > P5. \quad (1)$$

As illustrated in FIG. 6, each probability is associated with a specific transition. Alternate probability assignments are also possible, wherein a transition probability may be associated with multiple possible transitions. The upper row illustrates the transition probabilities for increases in data rate when the system is determined as not busy. The not busy indication may be made by a message or bit from the transmitter on the FL, or may be based on a measurement of channel quality or some other link criteria. FL channel quality considerations are discussed hereinbelow. The lower row illustrates the transition probabilities corresponding to decreases in data rates when the system is determined to be busy. Again, the busy indication may be made by a message or bit from the transmitter on the FL, or may be based on a measurement of channel quality or

some other link criteria. The last data rate on the right corresponds to the maximum data rate. In the system discussed herein as an example, the system supports four data rates. It is possible to limit the maximum data rate, in which case the total number of available data rates is reduced.

[0032] The transition probabilities are therefore used to determine a data rate decision of the CLRA calculation. In effect, the CLRA associated data rate R_3 will be R_{OLD} , $(R_{OLD}/2)$, $(R_{OLD}*2)$, limiting the rate change. As discussed hereinabove, the AT then determines the minimum of the data rates R_1 , R_2 , R_3 , and R_4 , and applies the minimum data rate.

$$R_{NEW} = \min(R_1, R_2, R_3, R_4) \quad (2)$$

Adjust Maximum Data Rate

[0033] In one embodiment, the rate allocation algorithm is modified to consider the FL serving sector SINR as measured and/or estimated at the AT. The FL serving sector SINR is used to limit the maximum data rate allowable for RL transmissions of the AT. FIG. 7 illustrates a table identifying the associated maximum data rate for the RL as a function of FL SINR values. The illustrated table includes three SINR value ranges: 1) less than 0dB; 2) from 0dB to 4dB; and 3) greater than 4dB. Note that alternate embodiments may implement a different number of ranges, as well as different ranges. The mapping of SINR value to maximum RL data rate may be a formula rather than a look up table. Similarly, alternate maximum RL data rates may be implemented. Also indicate that 5 max rate levels can be used as we have 5 defined rates on the RL. It should also be made clear that additional levels may be used if additional rates are added on the RL.

[0034] The system 100 supports the IS-856 standard, and therefore, each AT determines a data rate for the FL as a function of the FL quality, such as by use of the FL SINR. The AT then sends a data rate request on a Data Rate Channel (DRC). The DRC data rate request indicates the data rate at which the AT is able to receive data communications. The AN then uses this information to schedule transmissions to ATs for which data is pending at the AN. As the data rate request is determined in response to the FL SINR, the DRC data rate request may be used to determine the maximum RL data rate.

[0035] In another embodiment, the maximum RL data rate may be limited as a function of the RL channel state. In system 100, supporting the 1xEV-DO standard, the ATs are required to continually transmit a RL pilot signal. The RL pilot signal is transmitted on a pilot channel, which is power controlled. The RL traffic channel is power controlled based on the RL pilot, i.e., the RL traffic channel power is relative to the pilot channel power and the traffic-channel-to-pilot-channel power ratios are predetermined. Variations on the pilot channel are due to changes in channel conditions. The variations in power on the traffic channel are those on the pilot channel as well as due to the bursty-nature of packet data transmissions. For this reason, large changes in the RL pilot power corresponds to a RL channel state change, i.e., change in RL channel quality. Sudden changes in RL channel conditions may result in increased interference to terminals in adjacent sectors. This algorithm avoids sudden changes in RL channel conditions from resulting in increased interference by limiting the max. RL transmit rate in case of sudden changes in RL channel conditions, e.g., if the AT transmits at high rates in good channel conditions, sudden degradation in channel condition (which is OK for the RL to the power controlling sector) the AT continuing to transmit at high RL rates may result in higher levels of interference to terminals in adjacent sectors.

[0036] If the instantaneous RL pilot power (transmit power) is above a given threshold with respect to the average pilot power, the maximum RL data rate is limited to a given data rate. The data rate may be limited to a predetermined data rate or may be calculated as a function of the current data rate, loading of the system, or some other parameter. The use of the RL channel state information may be implemented with the FL channel quality information to limit the maximum RL data rate.

[0037] In still another embodiment, the maximum RL data rate may be limited by the AN, wherein the AN measures the differential Rise-Over-Thermal (ROT) between neighboring sectors. The ROT is a metric calculated for a sector *i*, given as:

$$ROT = \frac{I_{0_i}}{N_{0_i}} = \frac{\text{total received power}}{\text{thermal noise floor}} \quad (3)$$

wherein the subscript “*i*” indicates the sector *i*. A comparison of ROT values for neighboring sectors, such as sectors *i* and *j*, is given as:

$$\Delta ROT = \frac{I_{0_i}}{N_{0_i}} - \frac{I_{0_j}}{N_{0_j}} \quad (4)$$

With respect to FIG. 1, a comparison of the ROT for sectors 112 and 114 is performed at a Base Station Controller (BSC) (not shown). Each BS sends an ROT value corresponding to the sector served by the BS. The BSC may then adjust the maximum RL data rate and/or transition probabilities for Access Terminals (ATs) within the sectors. As an example, consider a system incorporating a predetermined target r_t , wherein an ROT that is greater than 3dB above the target r_t indicates a loaded condition for that sector. If a first sector has an ROT calculated as $r_1 = r_t - 3\text{dB}$, and a second sector has an ROT calculated as $r_2 = r_t + 3\text{dB}$, then the BSC may decide to implement a plan as follows. For a MS having an Active Set (AS) containing sector 1 but not sector 2, the BSC may lower the maximum data rate of the MS. The MS is in communication with sector 1, which is not loaded, but is not able to utilize sector 2, which is not loaded. Therefore, unless the MS is limited to a lower maximum data rate it may cause significant interference.

[0038] If the differential ROT exceeds a threshold, terminals that have only the lightly loaded sector in their active set are required to limit their max rate. In one embodiment, the maximum RL data rate is set to 38.4 kbps. In an alternate embodiment, the AT measures the captured SINR which is the sum total of the forward link SINR received at the AT. The captured SINR is used to determine if adjustment is made to the transition probabilities stored at the AT. For captured SINR above a target threshold, the AT may adjust the maximum data rate to allow higher data rates. Conversely, for captured SINR below a target threshold, the AT may adjust the maximum data rate to limit the AT to lower data rates. Two distinct thresholds may be used for the two cases given.

Adjusting RL Transition Probabilities in Response to FL Channel Condition

[0039] In another embodiment, different sets of RL data rate transition probabilities are assigned to ATs as a function of the FL sector SINR. The rate shaping may be implemented adjusting the transition probabilities in response to perceived channel quality. Improved channel quality will result in transition probabilities that encourage increases in RL data rates. Degraded channel quality will result in transition

probabilities that encourage decreases in RL data rates. Such probabilistic rate shaping may also be applied to maximum RL data rate limiting as a function of SINR.

[0040] Each AT measures the channel quality of the FL received signal. In response thereto, the AT may choose to maintain the current values of the transition probabilities, as illustrated in FIG. 6, or may choose to adjust one or more of the probabilities. For example, if the channel quality measurement, such as an SINR measurement, is above a predetermined threshold, the probabilities may be changed to encourage higher data rates. In other words, the transition probabilities may be modified to increase the probability of making the associated transitions. Similarly, if the channel quality measurement is below another such threshold, the transition probabilities are adjusted to discourage higher data rates. Note that a single threshold may be used, or a range of values, wherein for quality measurement values within the range of values the current transition probabilities are maintained, and for quality measurement values outside the range of values the current transition probabilities are adjusted. In one embodiment, each individual transition, e.g., p1, p2, etc., has an associated threshold or thresholds for adjustment decisions. In addition to adjusting the transition thresholds, or instead of adjusting the transition thresholds, the AT may adjust the maximum allowable data rate in response to a channel quality measurement. This may result in the addition of data rates, and thus additional transition probabilities for those rates, or may result in the elimination of data rates, and thus the elimination of the transitional probabilities associated with the eliminated data rates. For example, as illustrated in FIG. 6, if the maximum rate for the AT is reduced to 76.8kbps, then the rate 153.6 kbps is ignored or eliminated, as are the transition probabilities P4 and Q4 respectively. The RL transition probabilities may be adjusted based on captured SINR or RL channel conditions.

[0041] FIG. 8 illustrates an AT 200 configured for RL rate allocation as a function of FL channel quality. AT 200 includes receive circuitry 202 and transmit circuitry 204, each coupled to a communication bus 210. The receive circuitry 202 provides a received sample to FL quality measure unit 206 which determines the FL quality based on samples received via the FL. The FL quality measure unit 206 may measure/estimate SINR or some other parameter associated with link quality. The AT 200 also includes a data queue 208 that stores data pending for transmission by AT 200, a memory 216 that stores tables and other information associated with data rate

allocation on the RL. A RL data rate select unit 212 is also coupled to the communication bus 210 and determines a RL data rate as a function of the FL channel quality. Note that RL data rate select unit 212 performs any of the intermediate calculations required to determine a data rate, such as the steps of the data rate allocation algorithm discussed hereinabove. For example, data rate allocation may involve determining a maximum data rate, the amount of data pending, the transmit power, and/or CLRA calculations. A Power Control (PC) unit 218 is coupled to the communication bus 210 and implements a PC mechanism to adjust the transmit power of the AT 200. An RAB filter 214 tracks the historical system loading information. A processor 220 controls the various functions of AT 200. Alternate embodiments may include some or all of the functional blocks described in FIG. 8. Additional functional blocks may be implemented within AT 200. Note that while FIG. 8 illustrates all functional blocks communicating through a communication bus 210, alternate configurations may implement direct connections between functional blocks as desirable.

[0042] FIG. 9 illustrates an infrastructure element of AN 300, which may be a Base Station Controller (BSC). A communication bus 310 is illustrated to facilitate communication and exchange of information within the AN infrastructure element 300. Receive circuitry 302 and transmit circuitry 312 are each coupled to communication bus 310. A ROT calculation unit 304 determines the ROT of each of multiple neighboring sectors and determines a maximum RL rate limit in response. A PC unit 306 controls RL power control and generates PC instructions for each AT. A FL data scheduler 308 schedules transmissions to the various ATs on the FL. A memory 318 and processor 314 are also coupled to communication bus 310. The RAB generator 316 determines the loading of the system and generates the RAB in response.

[0043] In an alternate embodiment, a BSC receives ROT from multiple BSs, as discussed hereinabove. The BSC compares neighboring sector ROT values. The BSC may then adjust the transition probabilities of ATs within a given sector based on the comparison information. For example, the BSC may adjust the transition probabilities of those ATs that only have the unloaded sector in their active set and are not able to utilize the loading information from a loaded neighboring sector, so as to encourage lower data rates.

[0044] In an alternate embodiment, the AT measures the captured SINR which is the sum total of the forward link SINR received at the AT. The captured SINR is used to determine if adjustment is made to the transition probabilities stored at the AT. For captured SINR above a target threshold, the AT may adjust the transition probabilities to encourage higher data rates. Conversely, for captured SINR below a target threshold, the AT may adjust the transition probabilities to discourage higher data rates. Two distinct thresholds may be used for the two cases given.

[0045] Note that the functional blocks are provided to illustrate the functionality of the AT 200 and infrastructure element 300, and therefore, alternate embodiments may implement such functionality in different configurations.

[0046] Those of skill in the art would understand that information and signals may be represented using any of a variety of different technologies and techniques. For example, data, instructions, commands, information, signals, bits, symbols, and chips that may be referenced throughout the above description may be represented by voltages, currents, electromagnetic waves, magnetic fields or particles, optical fields or particles, or any combination thereof.

[0047] Those of skill would further appreciate that the various illustrative logical blocks, modules, circuits, and algorithm steps described in connection with the embodiments disclosed herein may be implemented as electronic hardware, computer software, or combinations of both. To clearly illustrate this interchangeability of hardware and software, various illustrative components, blocks, modules, circuits, and steps have been described above generally in terms of their functionality. Whether such functionality is implemented as hardware or software depends upon the particular application and design constraints imposed on the overall system. Skilled artisans may implement the described functionality in varying ways for each particular application, but such implementation decisions should not be interpreted as causing a departure from the scope of the present invention.

[0048] The various illustrative logical blocks, modules, and circuits described in connection with the embodiments disclosed herein may be implemented or performed with a general purpose processor, a digital signal processor (DSP), an application specific integrated circuit (ASIC), a field programmable gate array (FPGA) or other programmable logic device, discrete gate or transistor logic, discrete hardware

components, or any combination thereof designed to perform the functions described herein. A general purpose processor may be a microprocessor, but in the alternative, the processor may be any conventional processor, controller, microcontroller, or state machine. A processor may also be implemented as a combination of computing devices, e.g., a combination of a DSP and a microprocessor, a plurality of microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration.

[0049] The steps of a method or algorithm described in connection with the embodiments disclosed herein may be embodied directly in hardware, in a software module executed by a processor, or in a combination of the two. A software module may reside in RAM memory, flash memory, ROM memory, EPROM memory, EEPROM memory, registers, hard disk, a removable disk, a CD-ROM, or any other form of storage medium known in the art. An exemplary storage medium is coupled to the processor such the processor can read information from, and write information to, the storage medium. In the alternative, the storage medium may be integral to the processor. The processor and the storage medium may reside in an ASIC. The ASIC may reside in a user terminal. In the alternative, the processor and the storage medium may reside as discrete components in a user terminal.

[0050] The previous description of the disclosed embodiments is provided to enable any person skilled in the art to make or use the present invention. Various modifications to these embodiments will be readily apparent to those skilled in the art, and the generic principles defined herein may be applied to other embodiments without departing from the spirit or scope of the invention. Thus, the present invention is not intended to be limited to the embodiments shown herein but is to be accorded the widest scope consistent with the principles and novel features disclosed herein.

WHAT IS CLAIMED IS:

CLAIMS

1. A method for reverse link rate allocation in a wireless communication system, comprising:
 - determining channel quality of a forward link;
 - determining a maximum reverse link data rate as a function of the channel quality of the forward link; and
 - transmitting data on the reverse link at a data rate less than or equal to the maximum reverse link data rate.
2. The method as in claim 1, wherein determining the channel quality of the forward link comprises measuring a signal-to-noise ratio of the forward link of a serving sector, and
wherein determining the maximum reverse link data rate comprises comparing the signal-to-noise ratio of the forward link of the serving sector to a threshold.
3. The method as in claim 2, wherein the reverse link supports a plurality of data rates, and wherein transition probabilities are assigned to transitions between the plurality of data rates.
4. The method as in claim 1, wherein determining channel quality comprises determining channel quality of a forward link by measuring a captured signal to noise ratio of the forward link.
5. A method for reverse link rate allocation in a wireless communication system, comprising:
 - determining a data rate control request identifying a data rate for the reverse link;
 - determining a maximum reverse link data rate as a function of the data rate control request; and
 - transmitting data on the reverse link at a data rate less than or equal to the maximum reverse link data rate.

6. A method for reverse link rate allocation in a wireless communication system, comprising:
- determining channel quality of a reverse link;
 - determining a maximum reverse link data rate as a function of the channel quality of the reverse link; and
 - transmitting data on the reverse link at a data rate less than or equal to the maximum reverse link data rate.
7. A method for reverse link rate allocation in a wireless communication system, comprising:
- receiving a first rise over thermal value from a first base station associated with a first sector;
 - receiving a second rise over thermal value from a second base station associated with a second sector, wherein the first sector and second sector are neighboring sectors;
 - comparing the first rise over thermal value to the second rise over thermal value; and
 - setting a reverse link maximum data rate based on comparing the first rise over thermal value to the second rise over thermal value.
8. An apparatus for reverse link rate allocation in a wireless communication system, comprising:
- means for determining channel quality of a forward link;
 - means for determining a maximum reverse link data rate as a function of the channel quality of the forward link; and
 - means for transmitting data on the reverse link at a data rate less than or equal to the maximum reverse link data rate.
9. The apparatus as in claim 8, wherein the means for determining the channel quality of the forward link comprises means for measuring a signal-to-noise ratio of the forward link, and

wherein the means for determining the maximum reverse link data rate comprises means for comparing the signal-to-noise ratio of the forward link to a threshold.

10. The apparatus as in claim 9, wherein the reverse link supports a plurality of data rates, and wherein transition probabilities are assigned to transitions between the plurality of data rates.

11. An apparatus for reverse link rate allocation in a wireless communication system, comprising:

means for determining a data rate control request identifying a data rate for the reverse link;

means for determining a maximum reverse link data rate as a function of the data rate control request; and

transmitting data on the reverse link at a data rate less than or equal to the maximum reverse link data rate.

12. The apparatus as in claim 11, wherein the means for determining the data rate control request comprises:

means for measuring a signal-to-noise ratio of a forward link; and

means for comparing the signal-to-noise ratio of the forward link to a threshold.

13. An apparatus for reverse link rate allocation in a wireless communication system, comprising:

means for determining channel quality of a reverse link;

means for determining a maximum reverse link data rate as a function of the channel quality of the reverse link; and

means for transmitting data on the reverse link at a data rate less than or equal to the maximum reverse link data rate.

14. The apparatus as in claim 13, wherein the means for determining the channel quality of the reverse link comprises:

means for transmitting a reverse link pilot signal having an associated transmit pilot power;

means for calculating an average transmit pilot power of the reverse link;

means for calculating an instantaneous transmit pilot power of the reverse link;

means for comparing the instantaneous transmit pilot power of the reverse link to the average transmit pilot power of the reverse link.

15. The apparatus as in claim 14, wherein calculating the average transmit pilot power of the reverse link comprises filtering the transmit pilot power over a first number of time slots.

16. An apparatus for reverse link rate allocation in a wireless communication system, comprising:

means for measuring a first rise over thermal value of the forward link for a first sector;

means for measuring a second rise over thermal value of the forward link for a second sector;

means for comparing the first rise over thermal value to the second rise over thermal value; and

means for setting a reverse link maximum data rate based on comparing the first rise over thermal value to the second rise over thermal value.

17. The apparatus as in claim 16, wherein the first and second sectors are neighbors.

18. The apparatus as in claim 17, wherein the means for setting the reverse link maximum data rate comprises:

means for determining a difference between the first and second rise over thermal values; and

means for comparing the difference to a threshold.

19. An apparatus for reverse link rate allocation in a wireless communication system, comprising:

memory storage device adapted to store computer-readable instructions; and
a processing unit coupled to the memory storage device and adapted for:
determining channel quality of a forward link;
determining a maximum reverse link data rate as a function of the
channel quality of the forward link; and
transmitting data on the reverse link at a data rate less than or equal
to the maximum reverse link data rate.

20. An apparatus for reverse link rate allocation in a wireless communication system, comprising:

memory storage device adapted to store computer-readable instructions; and
a processing unit coupled to the memory storage device and adapted for:
determining a data rate control request identifying a data rate for the
reverse link;
determining a maximum reverse link data rate as a function of the
data rate control request; and
transmitting data on the reverse link at a data rate less than or equal
to the maximum reverse link data rate.

21. An apparatus for reverse link rate allocation in a wireless communication system, comprising:

memory storage device adapted to store computer-readable instructions; and
a processing unit coupled to the memory storage device and adapted for:
measuring a first rise over thermal value of the forward link for a first
sector;
measuring a second rise over thermal value of the forward link for a
second sector;
comparing the first rise over thermal value to the second rise over
thermal value; and
setting a reverse link maximum data rate based on comparing the first
rise over thermal value to the second rise over thermal value.

22. A method for reverse link rate allocation in a wireless communication system supporting a plurality of data rates, the data rates having a corresponding set of transition probabilities for transitions between the plurality of data rates, the method comprising:

- adjusting at least one of the transition probabilities; and
- applying the transition probabilities to determine a transmit data rate for the reverse link.

23. A method for reverse link rate allocation in a wireless communication system supporting a plurality of data rates, the data rates having a corresponding set of transition probabilities for transitions between the plurality of data rates, the method comprising:

- determining a desired rate profile;
- adjusting at least one of the transition probabilities to achieve the desired rate profile; and
- transmitting the transitional probabilities via a radio link.

24. The method as in claim 23, wherein the rate profile describes the throughput of the system as a function of channel quality.

25. The method as in claim 24, wherein the rate profile describes the throughput of the system as a function of distance from an access terminal.

26. An apparatus for reverse link rate allocation in a wireless communication system supporting a plurality of data rates, the data rates having a corresponding set of transition probabilities for transitions between the plurality of data rates, the apparatus comprising:

- means for adjusting at least one of the transition probabilities; and
- means for applying the transition probabilities to determine a transmit data rate for the reverse link.

27. An apparatus for reverse link rate allocation in a wireless communication system supporting a plurality of data rates, the data rates having a corresponding set of transition probabilities for transitions between the plurality of data rates, the apparatus comprising:

- means for determining a desired rate profile;
- means for adjusting at least one of the transition probabilities to achieve the desired rate profile; and
- means for transmitting the transitional probabilities via a radio link.

28. The apparatus as in claim 27, wherein the rate profile describes the throughput of the system as a function of channel quality.

29. The method as in claim 28, wherein the rate profile describes the throughput of the system as a function of distance from an access terminal.

30. An apparatus for reverse link rate allocation in a wireless communication system supporting a plurality of data rates, the data rates having a corresponding set of transition probabilities for transitions between the plurality of data rates, the apparatus comprising:

- memory storage device adapted to store computer-readable instructions; and
- a processing unit coupled to the memory storage device and adapted for:
 - adjusting at least one of the transition probabilities; and
 - applying the transition probabilities to determine a transmit data rate for the reverse link.

31. An apparatus for reverse link rate allocation in a wireless communication system supporting a plurality of data rates, the data rates having a corresponding set of transition probabilities for transitions between the plurality of data rates, the apparatus comprising:

- memory storage device adapted to store computer-readable instructions; and
- a processing unit coupled to the memory storage device and adapted for:
 - determining a desired rate profile;

adjusting at least one of the transition probabilities to achieve the desired rate profile; and
transmitting the transitional probabilities via a radio link.

32. An apparatus for reverse link rate allocation in a wireless communication system supporting a plurality of data rates, the data rates having a corresponding set of transition probabilities for transitions between the plurality of data rates, the apparatus comprising:

memory storage device adapted to store computer-readable instructions; and
a processing unit coupled to the memory storage device and adapted for:
determining a desired rate profile;
adjusting at least one of the transition probabilities to achieve the desired rate profile; and
transmitting the transitional probabilities via a radio link.

33. A method for reverse link rate allocation in a wireless communication system supporting a plurality of data rates, the data rates having a corresponding set of transition probabilities for transitions between the plurality of data rates, the method comprising:

receiving a first rise over thermal value from a first base station associated with a first sector;
receiving a second rise over thermal value from a second base station associated with a second sector, wherein the first sector and second sector are neighboring sectors;
comparing the first rise over thermal value to the second rise over thermal value;
and
adjusting the set of transition probabilities based on comparing the first rise over thermal value to the second rise over thermal value.

34. The method as in claim 33, wherein the first and second sectors are neighbors.

35. The method as in claim 34, wherein adjusting the set of transition probabilities comprises:

- determining a difference between the first and second rise over thermal values;
- and
- comparing the difference to a threshold.

36. An apparatus for reverse link rate allocation in a wireless communication system supporting a plurality of data rates, the data rates having a corresponding set of transition probabilities for transitions between the plurality of data rates, the apparatus comprising:

- means for receiving a first rise over thermal value from a first base station associated with a first sector;
- means for receiving a second rise over thermal value from a second base station associated with a second sector, wherein the first sector and second sector are neighboring sectors;
- means for comparing the first rise over thermal value to the second rise over thermal value; and
- means for adjusting the set of transition probabilities based on comparing the first rise over thermal value to the second rise over thermal value.




FIG. 1





FIG. 2A

FIG. 2B



BEST AVAILABLE COPY

RATE INDEX	DATA RATE
1	9.6
2	19.2
3	38.4
4	76.8
5	153.6

FIG. 3

$$P_{up} = [P_0 \ P_1 \ P_2 \ P_3 \ P_4]$$
$$P_{DN} = [P_5 \ P_6 \ P_7 \ P_8 \ P_9]$$
$$INDEX = \begin{matrix} \uparrow & \uparrow & \uparrow & \uparrow & \uparrow \\ 1 & 2 & 3 & 4 & 5 \end{matrix}$$

FIG. 4




FIG. 5

<0dB	38.4 kbps	3
0dB - 4dB	76.8kbps	4
> 4dB	153.6kbps	5

FIG. 7

5/7




FIG. 6




FIG. 8




FIG. 9

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ BLACK BORDERS
- ☐ IMAGE CUT OFF AT TOP, BOTTOM OR SIDES
- ☐ FADED TEXT OR DRAWING
- ☒ BLURRED OR ILLEGIBLE TEXT OR DRAWING
- ☐ SKEWED/SLANTED IMAGES
- ☐ COLOR OR BLACK AND WHITE PHOTOGRAPHS
- ☐ GRAY SCALE DOCUMENTS
- ☐ LINES OR MARKS ON ORIGINAL DOCUMENT
- ☐ REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY
- ☐ OTHER: _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.

THIS PAGE BLANK (USPTO)